

Kenwood Protalk and Motorola RDX Frequency Comparison Chart

UHF Radio Comparison Chart

Channel	Kenwood TK3300LU16P	Tone Code#	Table #	Channel	Motorola RDU2080d	Tone Code#	Table #
*1	464.5500	67.0 (1)	2	*1	464.5500	67.0 (1)	2
*2	467.9250	67.0 (1)	8	*2	467.9250	67.0 (1)	8
*3	461.0375	67.0 (1)	9	3	467.8500	67.0 (1)	5
*4	461.0625	67.0 (1)	10	4	467.8750	67.0 (1)	6
5	461.0875	67.0 (1)	11	5	461.0625	67.0 (1)	10
6	461.1125	67.0 (1)	12	6	461.1125	67.0 (1)	12
7	461.1375	67.0 (1)	13	7	461.1625	67.0 (1)	14
8	461.1625	67.0 (1)	14	8	461.2125	67.0 (1)	16
9	464.5000	67.0 (1)	1				
10	467.7625	67.0 (1)	3				
11	467.8125	67.0 (1)	4				
12	467.8500	67.0 (1)	5				
13	467.8750	67.0 (1)	6				
14	467.9000	67.0 (1)	7				
15	461.1875	67.0 (1)	15				
16	461.2125	67.0 (1)	16				

*Kenwood TK-3300LU4P uses the same first 4 channels

*Motorola RDU2020 uses the same first 2 channels

VHF Radio Comparison Chart

Channel	Kenwood TK2300LU16P	Tone Code#	Table #	Channel	Motorola RDV2080d	Tone Code#	Table #
*1	154.9000	67.0 (1)	20	*1	154.9000	67.0 (1)	20
*2	154.5150	67.0 (1)	21	*2	154.5150	67.0 (1)	21
*3	151.6250	67.0 (1)	1	3	151.6250	67.0 (1)	1
*4	151.9550	67.0 (1)	2	4	151.9550	67.0 (1)	2
5	151.5125	67.0 (1)	10	5	151.5125	67.0 (1)	10
6	151.6850	67.0 (1)	12	6	151.6850	67.0 (1)	12
7	151.7750	67.0 (1)	15	7	151.7750	67.0 (1)	15
8	158.4000	67.0 (1)	26	8	158.4000	67.0 (1)	26
9	151.6250	77.0 (4)	1				
10	151.6250	88.5 (8)	1				
11	151.6250	179.9 (29)	1				
12	151.9550	82.5 (6)	2				
13	151.9550	94.8 (10)	2				
14	151.9550	179.9 (29)	2				
15	151.7000	67.0 (1)	5				
16	151.7600	67.0 (1)	6				

*Kenwood TK-2300LU4P uses the same first 4 channels

*Motorola RDV2020 uses the same first 2 channels