

PROFESSIONAL
SERIES

blackbox™
2-way radios



FEATURES

- ▶ UHF or VHF
- ▶ 16 Channels
- ▶ 5 / 4 / 2 Watts
- ▶ Scanning
- ▶ Voice Channel Enumeration
- ▶ PC Program Freqs, PL, DPL
- ▶ Programmable Buttons:
 - Voice Encryption Function
 - Alarm Function
 - Whisper Transmit Function
 - High/Low Power

NARROWBAND COMPLIANT



Custom Silicone
& Ballistic Nylon
Cases

Specifications

General

| | |
|------------------------------|------------------------------------|
| Frequency Range | UHF: 400-470MHz VHF: 136-174MHz |
| Channel Capacity | 16 (15+S) |
| Channel Spacing | 25.0kHz / 12.5kHz |
| Frequency Stability | ±2.5PPM |
| Operating Temperature | -25--+55°C |
| Antenna Impedance | 50Ω |
| Li-Ion Battery | 1500mAh |
| Operation Voltage | 7.5V |
| Dimensions (WxHxD) | 2.3" x 3.75" x 1.34" |
| Weight (w/antenna & battery) | 6.98 oz or 198g |

Transmitter

| | |
|----------------|-----------------------|
| RF Power (H/L) | UHF: 4W/2W VHF: 5W/2W |
|----------------|-----------------------|

Receiver

| | |
|------------------------------|-----------------|
| Audio Distortion | ≤5% |
| Reference Sensitivity | 0.15uV / 0.18uV |
| Adjacent Channel Selectivity | 65dB / 55dB |
| Intermodulation Reject Ratio | 55dB |
| Audio Power Output | Maximum: ≥0.6W |



3.75"

BANTAM® 2-Way Radio

- Includes battery, rapid charger, antenna, belt clip
- Specify UHF or VHF - programming available



FCC ID: U7GBLACKBOXBU
FCC ID: U7GBLACKBOXBV

Now Available for Canada
IC # 6388A-Bantam UHF
IC # 6388A-Bantam VHF

