



One of the most affordable, durable, and feature packed two-way radios available.

AWR ADVANTAGE™

TWO-WAY BUSINESS RADIO

Feature packed, the AWR Advantage Two-way Business Radio is a workhorse. You won't believe everything this radio can do. Some of the unique features of this radio includes: LED flashlight, channel aliases, programmable power - up to 2 Watts, and more!

On top of that customize the faceplates with your company's logo and color.

Key Features:

- Black Housing
- 16 Channels
- 2 Watts (programmable to low/med/high)
- Customizable Face Plate
- Audio Channel Annunciation
- Alphanumeric Display
- Busy Channel Lockout (BCL)
- Time-Out-Timer (TOT)
- LED Flashlight
- Speaker Enable / Disable
- Scan (user selectable)
- Priority Scan
- Programmable Mic Sensitivity
- PC Programmable or by Hand
- Wireless Clone
- Programmable Key Functions
- Menu Programmable Mode
- Radio Power On Text
- Battery Save Mode
- Low Battery Alert
- 9 Programmable Call Tones
- Audio Compandor
- Audio Scrambler
- VOX
- Motorola CLS Compatible (accessories)



AWR Advantage
(with holster & battery)
106094

Accessories:



Yellow Faceplate
221060



Green Faceplate
221056



Blue Faceplate
221057



Red Faceplate
221055



Purple Faceplate
221058



Battery
221051



Single Unit Charger
221052



Six Unit Charger
221053



Black Faceplate
221054



Silver Faceplate
221059




Holster Belt Clip
221115



Rubber Sleeve
221050



Belt Clip
221049



Reversible Ear Hook
221108

Additional accessories including wired headsets are available. Please contact dealer below.

Specifications:

Housing Color	Black
Dimension (inches)	
Height (including antenna)	5.8"
Width	2"
Depth	1.10"
Weight (w/battery & antenna)	4.5 oz
Antenna	Fixed
Audio Accessory Jack	Double Pin
Power Supply - Battery	1250 mAh (Li-Ion)
Power	0.5 / 1 / or 2 W
Channels	up to 16
Select Channels	Up/Down Buttons
Frequency	450-470MHz UHF Band
Battery Status Indicator	Yes
Built-in VOX	Yes
Battery Save Mode	Yes
TOT	Yes

Componder	Yes / Channel
Scan	Yes
Priority Scan	Yes
Busy Channel Lock-Out	Yes
Proceed to Talk Tone	Yes
Roger Tone	Yes
Scramble	Yes
LCD (with available aliases)	Yes - with Back Light
Vibration	Yes
Bluetooth	No
Voice Recorder	Yes
DTMF Encoding	Yes
CTCSS & DCS Coding	Yes
Keylock	Yes
Adjustable Microphone Gain (Sensitivity)	Yes
Wireless Cloning	Yes

Channel Spacing	12.5 KHz
Operating Voltage	3.7 V
Battery Life 5.5.90 Battery Save - ON	Low - 18 hours Medium - 16 hours High - 14 hours
Frequency Stability	±2.5ppm
Operating Temperature	-20°C to +55°C
Antenna Impedance	50Ω
Modulation	11K0F3E/6K00F3E
Spurious and Harmonics	≤-36dBm
FM Noise	≥40dB
Audio Distortion	≤5%
Sensitivity	0.25 μV
Selectivity	55dB
Inter Modulation	60dB
S/N	≥45dB
Rated Audio Power Output	500mW

900270

HiTechWireless

Tel: 888.511.5162

Fax: 866.341.3315

sales@hitechwireless.com

HiTechWireless.com